An Arduino Based Heartbeat Detection Device (ArdMob-ECG) for Real-Time ECG Analysis

T. Möller^{1,2}, Y. Georgie³, M. Voss^{2,4} and L. Kaltwasser^{1,2}

Berlin School of Mind and Brain, Humboldt-Universität zu Berlin, Germany
 Department for Psychiatry and Psychotherapy, Charité University Medicine, Berlin, Germany
 Department of Computer Science, Humboldt-Universität zu Berlin, Germany
 4. St. Hedwig Krankenhaus, Berlin, Germany
 {tim.julian, laura.kaltwasser}@hu-berlin.de,
 yasmin.kim.georgie@informatik.hu-berlin.de, martin.voss@charite.de

This technical paper provides a tutorial to build a low-cost (10-100 USD) and easy to assemble ECG device (ArdMob-ECG) that can be easily used for a variety of different scientific studies. The advantage of this device is that it automatically stores the data and has a built-in detection algorithm for heartbeats. Compared to a clinical ECG, this device entails a serial interface that can send triggers via USB directly to a computer and software (e.g. Unity, Matlab) with minimal delay due to its architecture. Its software and hardware is open-source and publicly available. The performance of the device regarding sensitivity and specificity is comparable to a professional clinical ECG and is assessed in this paper. Due to the open-source software, a variety of different research questions and individual alterations can be adapted using this ECG. The code as well as the circuit is publicly available and accessible for everyone to promote a better health system in remote areas, Open Science, and to boost scientific progress and the development of new paradigms that ultimately foster innovation.

The poster describes an Arduino-based heartbeat detection device (ArdMob-ECG) that integrates the AD8232 module for real-time ECG analysis. The ArdMob-ECG is easy to assemble, light-weight, small and transportable, inexpensive, yet reliable, and can be used without clinical personnel with simple instructions. This paper is meant as a guide for scientists to independently assemble the device for their own scientific studies. Utilizing an easy to use, inexpensive, lightweight, and reliable technical device for measuring heart rate and its components would advance the progress in scientific research. An ECG can monitor the heart activity of an individual and detect e.g. arrhythmias that can indicate heart problems. This has an immense meaning for monitoring the participants cardiac health.

The ArdMob-ECG described in this paper utilizes the AD8232 module, a small chip measuring the

electrical signal of the heart that is then translated to an ECG waveform. It implements a simplification of the Pan-Tompkins algorithm to calculate the occurrence of heartbeats in near real time. Different data (e.g. timestamps, raw data) can be saved on a built-in micro SD card, while other data such as triggers can be sent directly to another device using a serial interface (USBconnection). Thus, triggers can be sent with minimal delay. The heartbeat analysis can already be calculated locally on the Arduino. The Arduino can also provide auditory feedback whenever a heartbeat is detected. This tone can also be easily adjusted to occur faster, slower or with a specific delay to the actual heartbeat, depending on the scientific paradigm (e.g. the widely used interoceptive sensitivity paradigm [1]).



Figure 1. (a) The device how it is used. (b) The ArdMob-ECG inside the aluminium case showing the insides with the modules and all the relevant cable connections. The Piezo sound buzzer and the electrodes cable connected to the headphone jack of the AD8232 sensor can be seen on the right.

A major advantage of the ArdMob-ECG is that the variables can be easily modified, and additional triggers can be implemented, for example, directly playing the sounds faster or slower according to the last R-R interval [2][3][4].

To assess the quality of data obtained from the three channel ArdMob-ECG, data from 12 channel ECG from a clinical ECG machine (ZOLL X Series CCT Defibrillator) of a German ambulance and was

recorded simultaneously for three seconds on one healthy 24year-old participant. The ZOLL X Series CCT Defibrillator ECG-device is standard equipment and is routinely used in German ambulance vehicles. A trained medical expert compared both data outputs and assessed the validity of the heartbeat detection. Both devices managed to detect 100% of the heartbeats.

In light of growing development of sophisticated biofeedback methods in the health sciences, ECG data can provide valuable information about internal body states. Currently, the use of an ECG might be limited by expensive, heavy and rather immobile ECG machines, and difficulties in operating them with no technical training which might limit the overall progress in scientific biofeedback studies. Our mobile ECG device provides a solution to the aforementioned problems of high costs, transportability, and technical training required to operate a clinical ECG machine. Furthermore, the ArdMob-ECG allows for an easy way to save data and to send triggers through a direct interface with minimal temporal delay that can be of use for scientific paradigms.



Figure 2. (a) a schematic representation of a normal ECG consisting of the components P, Q, R, S, T. (b) A recording from the ArdMob-ECG device with the different components.

ACKNOWLEDGMENTS

This research was funded by the Deutsche

Forschungsgemeinschaft (DFG, German Research Foundation) – DFG – SPP – 2134. The pictures and the code for this device can be found in the GitHub repository [5]. The repository is licensed under the MIT license. Major sections of the Pan-Tompkins algorithm were adapted from an existing repository [6]. Some of the code contains elements from other available, open access, existing scripts, described in the Readme file in the GitHub repository. Author Contributions: T.J.M.: Conceptualization, software, validation, resources, writing original draft & editing, visualization; Y.K.G: Review & editing, visualization; M.V: Editing; L.K.: Editing.

REFERENCES

- [1] S. N. Garfinkel, A. K. Seth, A. B. Barrett, K. Suzuki, and H. D. Critchley, "Knowing your own heart: Distinguishing interoceptive accuracy from interoceptive awareness," *Biological Psychology*, vol. 104, pp. 65–74, Jan. 2015
- [2] J. Brener, X. Liu, and C. Ring, "A method of constant stimuli for examining heartbeat detection: Comparison with the Brener-Kluvitse and Whitehead methods," *Psychophysiology*, vol. 30, no. 6, pp. 657–665, Nov. 1993
- [3] K. Suzuki, S.N. Garfinkel, H.D. Critchley, and A. Seth. "Multisensory integration across exteroceptive and interoceptive domains modulates self-experience in the rubber-hand illusion." *Neuropsychologia*, vol. 51, no. 13, pp. 2909–2917, Nov. 2013.

- [4] S. Wiens and S. N. Palmer, "Quadratic trend analysis and heartbeat detection," *Biological Psychology*, vol. 58, no. 2, pp. 159–175, Nov. 2001
- [5] T. J. Möller, "Pan Tompkins QRS detector and Datalogger," Dec 2021, https://github.com/nalgi/ Pan-Tompkins_QRSdetector_and_Datalogger.
- [6] B. Milner, "Real Time QRS Detection," 2015, https://github. com/blakeMilner/real_time_QRS_detection.

An Arduino Based Heartbeat Detection Device (ArdMob-ECG) for Real-Time ECG Analysis

T. Möller^{1,2}, Y. Georgie³, M. Voss^{2,4} and L. Kaltwasser^{1,2}

1 Berlin School of Mind and Brain, Humboldt-Universität zu Berlin, Germany; 2 Department for Psychiatry and Psychotherapy, Charité University Medicine, Berlin, Germany; 3 Department of Computer Science, Humboldt-Universität zu Berlin, Germany;

4 St. Hedwig Krankenhaus, Berlin, Germany;

tim.julian.moeller@gmail.com

Abstract

This poster summarizes a technical paper [1] which provides a tutorial to build a low-cost (10-150 USD) and easy to assemble Arduino-based mobile ECG device which integrates the AD8232 module (ArdMob-ECG).

Introduction

The ArdMob-ECG is a **mobile solution for Electrocardiogram recording** and has the following advantages:

- . Small
- . Lightweight
- . Cost-efficient (~150 USD)
- . 3 electrodes instead of 12 needed
- . Can be battery-operated for mobile use
- . Reliable detection algorithm with sufficient sensitivity and reliability
- . Automatic saving on an inbuilt SD-card
- . Different data types can be saved on a built-in micro SD card
- Other data such as triggers can be sent directly to other devices or software using a serial interface (USB connection) with minimal delay
- C++ software adaptation allows for easy adjustments of the code. e.g. tones be played in synch or out of synch modified by length and pitch
- . Can be easily operated by non-clinical personell
- Open access Hard- and Software to promote open science and foster innovation





Figure 1: A picture of the ArdMob-ECG

Figure 1a: A picture of the ArdMob-ECG used in a VR study

Software & Hardware architecture

The ArdMob-ECG contains an Arduino that comes with its own software integrated development environment (IDE) and can be loaded via a USB cable to the Arduino board.

A variety of data types can be saved on a built-in micro SD card, while e.g. triggers can be sent directly to another device using a serial interface (USBconnection). The setup consists of an Arduino Mega 2560 board, an AD8232 heart beat monitor from which the cable for the electrodes connects, a 85 dB Piezo sound buzzer , and a micro SD memory card SPI reader.



HEADS AD8232 RLOPS AD8232 RL

Figure 2: A schematic diagram of the ArdMob-ECG.



Algorithm & Validation

The ArdMob-ECG software is based on a simplification of the Pan-Tompkins algorithm, used in [2]. The software provides an on board realtime analysis of the heartbeat, implementing the adaptive high pass and low pass filtering, and adaptive thresholding of the Pan-Tompkins algorithm, seen in Figure 3. Prerecorded ECGsignals taken from [3] were used to train the adaptive filtering and thresholding models prior to data collection in order to improve the detection accuracy.

The ArdMob ECG peak detection was compared to a professional ZOLL X Series CCT Defibrillator. Both devices managed to detect all the heartbeats, as evaluated by a trained paramedic. In Figure 4, an example peak, recorded by the ArdMob-ECG can be seen.





Figure 4: The different steps of the Pan-Tompkins algorithm [4,5,6]

Figure 5: An ideal schematic of an ECG (left) consisting of the components P,Q,R,S, and T (Picture taken from [7]). The right panel shows a recording from the ArdMob-ECG



Figure 6: The classic ECG electrode setup marked in black dots. Depicted in red dots are the three electrode placements that are needed for the ArdMob-ECG.

Conclusion

The mobile ArdMob-ECG provides a solution to the aforementioned problems of high costs, transportability, and technical training required to operate a clinical ECG machine. It can also be battery-operated and only requires 3 electrodes instead of 12.

Furthermore, the ArdMob-ECG allows for an easy way to save data and to send triggers through a direct interface with minimal temporal delay that can be of use for scientific paradigms.

References

 T.J. Möller, M. Voss, and L. Kaltwasser, "An Arduino based heartbeat detection device (ArdMob-ECG) for real-time ECG analysis," arXiv preprint arXiv:2204.00513, 2022



Scan the QR Code to access the paper.

^[2] H. Chen and S.-W. Chen, "A moving average based filtering system with its application to real-time QRS detection," Computers in cardiology, (pp. 585–588), 2003

^[3] B. Milner, "Real Time QRS Detection," 2015, (https://github.com/blakeMilner/real time QRS detection)

^[4] J. Pan and W. J. Tompkins, "A real-time QRS detection algorithm," IEEE transactions on biomedical engineering, no. 3, pp. 230–236, 1985.

⁽⁵⁾ H. Sedghamiz, "Complete Pan-Tompkins implementation ECG QRS detector," Mattab Central: Community Profile. Available online at: http://www.mathworks.com/mattabcentral/profile/authors/2510422-hooman-sedghamiz, vol. 172, 2014 [6] H. Sedghamiz, "Mattab implementation of pan tompkins ECG QRS detector," Code Available at the File Exchange Site of MathWorks, 2014.

^[7] R. Avanzato and F. Beritelli, "Automatic ecg diagnosis using convolutional neural network," Electronics, vol. 9, no. 6, p. 951, 2020.

AN ARDUINO BASED HEARTBEAT DETECTION DEVICE (ArdMob-ECG) FOR REAL-TIME ECG ANALYSIS

Tim J. Möller tim.julian.moeller@gmail.com https://www.timjmoeller.com/

03.12.2022

Tim J. Möller^{1,2}

¹ Berlin School of Mind and Brain, Humboldt-Universität zu Berlin, Germany
 ² Department for Psychiatry and Psychotherapy, Charité University Medicine, Berlin, Germany











The ArdMob-ECG is a mobile solution for Electrocardiogram recording

- Small
- Lightweight
- 3 electrodes instead of 12 needed
- Battery-operated for mobile use
- Reliable detection algorithm with sufficient sensitivity and reliability inbuilt
- Serial interface with minimal delay to connect to other machines and programs
- Automatic saving on an inbuilt SD-card



ADVANTAGES

- Triggers sent with minimal delay
- Data like timestamps, raw data, etc. can be saved on a built-in micro SD card
- Other data such as triggers can be sent directly to another device using a serial interface (USB connection)
- C++ software adaptation allows for easy adjustments of the code. e.g. tones be played in synch or out of synch modified by length and pitch



Schematic diagram of the ArdMob-ECG



Functional block module of the AD8232 heart rate sensor

Three electrode setup

- Only 3 compared to 12 electrodes of medical ECGs are necessary.
- The classic ECG electrode setup is marked by the black dots. Depicted as red dots are the three electrode place that are needed for the ArdMob-ECG.



ArdMob-ECG setup

5

VALIDATION

- The ArdMob-ECG captures the QRS heartbeat complex pattern
- The ArdMob-ECG peak detection results were compared to a medical ZOLL X Series CCT Defibrillator
- ArdMob-ECG detected all heartbeats, as evaluated by a trained paramedic

QRS complex recorded by the ArdMob-ECG

An ideal QRS complex

SOFTWARE

- The software utilizes a simplified version of the Pan-Tompkins algorithm
- Future perspective: Implementing further steps of the Pan-Tompkins algorithm to improve detection stability during body movement

The Pan-Tompkins algorithm

ArdMob-ECG USE IN SCIENTIFIC STUDIES

- The ArdMob-ECG can be used for a variety of applications, e.g. scientific experiments using Virtual reality. On the right side, the ECG can be seen.
- In the video at the bottom, an example paradigm is shown. Whenever a heartbeat is detected by the ArdMob-ECG, the virtual hands shortly flash in a red color in this paradigm

ArdMob-ECG **DOCUMENTATION**

Preprint:

https://arxiv.org/pdf/2204.00513v1.pdf

SCAN ME!

Cornell University	
arXiv > eess > arXiv:2204.00513	Search Help Ac
Electrical Engineering and Systems Science > Signal Processing	
[Submitted on 1 Apr 2022] An Arduino based heartbeat detection device (ArdMob-ECG) for real-time ECG anal	/sis

Tim Julian Möller, Martin Voss, Laura Kaltwasser

This technical paper provides a tutorial to build a low-cost (10-100 USD) and easy to assemble ECG device (ArdMob-ECG) that can be easily used for a variety of different scientific studies. The advantage of this device is that it automatically stores the data and has a built-in detection algorithm for heartbeats. Compared to a clinical ECG, this device entails a serial interface that can send triggers via USB directly to a computer and software (e.g. Unity, Matlab) with minimal delay due to its architecture. Its software and hardware is open-source and publicly available. The performance of the device regarding sensitivity and specificity is comparable to a professional clinical ECG. The code as well as the circuit is publicly available and accessible for everyone to promote a better health system in remote areas, Open Science, and to boost scientific progress and the development of new paradigms that ultimately foster innovation.

Subjects: Signal Processing (eess.SP); Hardware Architecture (cs.AR); Systems and Control (eess.SY) Cite as: arXiv:2204.00513 [eess.SP]

(or arXiv:2204.00513v1 [eess.SP] for this version) https://doi.org/10.48550/arXiv.2204.00513

Submission history

From: Tim Julian Möller [view email] [v1] Fri, 1 Apr 2022 15:14:33 UTC (10,243 KB)

POSTER

An Arduino Based Heartbeat Detection Device (ArdMob-ECG) for Real-Time ECG Analysis

T. Möller^{1,2}, Y. Georgie³, M. Voss^{2,4} and L. Kaltwasser^{1,2}

1 Berlin School of Mind and Brain, Humboldt-Universität zu Berlin, Germany; 2 Department for Psychiatry and Psychotherapy, Charité University Medicine, Berlin, Germany; 3 Department of Computer Science, Humboldt-Universität zu Berlin, Germany; 4 St. Hedwig Krankenhaus, Berlin, Germany; tim.julian.moeller@gmail.com

Abstract This poster summarizes a technical paper [1] which provides a tutorial to build a low-cost (10-150 USD) and easy to assemble Arduino-based mobile ECG device which integrates the AD8232 module (ArdMob-ECG).

Introduction The ArdMob-ECG is a mobile solution for Electrocardiogram recording and has the following advantages

. Small

. Lightweight

ECG

FCG

- . Cost-efficient (~150 USD)
- . 3 electrodes instead of 12 needed
- . Can be battery-operated for mobile use

. Reliable detection algorithm with sufficient sensitivity and reliability . Automatic saving on an inbuilt SD-card . Different data types can be saved on a built-in micro SD card Other data such as triggers can be sent directly to other devices or software using a serial interface (USB connection) with minimal delay

C++ software adaptation allows for easy adjustments of the code. e.g. tones be played in synch or out of synch modified by length and pitch . Can be easily operated by non-clinical personell . Open access Hard- and Software to promote open science and foster

Figure 1: A picture of the ArdMob-ArdMob-ECG used in a VR study

Software & Hardware architecture

The ArdMob-ECG contains an Arduino that comes with its own software integrated development environment (IDE) and can be loaded via a USB cable to the Arduino board.

A variety of data types can be saved on a built-in micro SD card, while e.g. triggers can be sent directly to another device using a serial interface (USBconnection). The setup consists of an Arduino Mega 2560 board, an AD8232 heart beat monitor from which the cable for the electrodes connects, a 85 dB Piezo sound buzzer, and a micro SD memory card SPI reader.

are used to train the adaptive filtering and thresholding models prior to data collection in order to improve the detection accuracy The ArdMob ECG peak detection was compared to a professional ZOLL X Series CCT Defibrillator. Both devices managed to detect all the heartbeats, as evaluated by a trained paramedic. In Figure 4, an

low pass filtering, and adaptive thresholding of the Pan-Tompkins algorithm, seen in Figure 3. Prerecorded ECGsignals taken from [3]

example peak, recorded by the ArdMob-ECG can be seen.

components P,Q,R,S, and T Figure 4: The different steps of the Pan-Tompkins algorithm [4,5,6] (Picture taken from [7]). The right panel shows a recording from the ArdMob-ECG

Figure 6: The classic ECG electrode setup marked in black dots. Depicted in red dots are the three electrode placements that are needed for the ArdMob-ECG.

Conclusion

The mobile ArdMob-ECG provides a solution to the aforementioned problems of high costs, transportability, and technical training required to operate a clinical ECG machine. It can also be battery-operated and only requires 3 electrodes instead of 12. Furthermore, the ArdMob-ECG allows for an easy way to save data and

to send triggers through a direct interface with minimal temporal delay that can be of use for scientific paradigms.

References

 T.J. Möller, M. Vois, and L. Kaltwasser, "An Arduino based heartbeat del analysis," arXiv preprint arXiv:2204.00513, 2022 analysis," arXiv preprint arXiv arXi [3] B. Miner, 'Real Time QRS Det ction," 2015, (https://githu J. Pan and W. J. Tompkins, "A real-time QRS detection algorithm," IEEE tra pp. 230–236, 1985. [6] H. Sedghamiz, 'Mada ntation of pan tompkins ECG QRS detector," Code Available at the File Ex [7] R. Avanzato 951, 2020. and F. Berthelli, "Automatic eco diagnosis using convolutional neural network," Electronica, vol. 9, no. 6, p.

Algorithm & Validation The ArdMob-ECG software is based on a simplification of the Pan-Tompkins algorithm, used in [2]. The software provides an on board realtime analysis of the heartbeat, implementing the adaptive high pass and

Contact me for further information and collaborations!

Tim J. Möller tim.julian.moeller@gmail.com https://www.timjmoeller.com/

